

API INTEGRATION

To Check Balance :

[http://bigerecharge.com/BAL.aspx?&userid=\[USERID\]&tpin=\[TRANSACTIONPIN\]](http://bigerecharge.com/BAL.aspx?&userid=[USERID]&tpin=[TRANSACTIONPIN])

Replace:

[USERID]= Mobile number of user register with our system

[TRANSACTIONPIN]=4 Digit Transaction Pin of user register with our system

To Check Balance Example :

<http://bigerecharge.com/BAL.aspx?&userid=9007650981&tpin=9505>

Response:

SUCCESS Balance= [amount]

Example: SUCCESS Balance= 10.00

To Recharge:

[http://bigerecharge.com/recharge2.aspx?&mob=\[MOBILE\]&prov=\[PROVIDERID\]&amt=\[AMOUNT\]&userid=\[USERID\]&tpin=\[TRANSACTIONPIN_\]](http://bigerecharge.com/recharge2.aspx?&mob=[MOBILE]&prov=[PROVIDERID]&amt=[AMOUNT]&userid=[USERID]&tpin=[TRANSACTIONPIN_])

Replace:

[MOBILE]=Customer Mobile Number to be recharged.

[PROVIDERID]= Unique Operator code as in the operator code table.

[AMOUNT]=Recharge amount.

[USERID]= Mobile number of user register with our system.

[TRANSACTIONPIN]=4 Digit Transaction Pin of user register with our system.

To Recharge Example:

<http://bigerecharge.com/recharge2.aspx?&mob=9836345671&prov=17&amt=10&userid=9007650981&tpin=9505>

Response:

IF Recharge Request is submitted Successfully Output is:

SUCC mob=[MOBILE] amt= [AMOUNT] RequestId= [REQUESTID]

[MOBILE]=Customer Mobile Number request for recharge.

[AMOUNT]=Recharge amount.

[REQUESTID]=Unique Id returned from system as response. It is required for status check.

Example:

SUCC mob= 9836851159 amt= 10 RequestId= 635206478450386096

IF Recharge Request is not submitted Successfully Error

Message are:

1. ERROR Recharge can't be processed.
2. ERROR Insufficient balance.
3. ERROR Please try after [time] minutes.
4. ERROR Recharge can't be processed.
5. ERROR Provider code is wrong.
6. ERROR Invalid Pin.
7. ERROR Invalid User Id.
8. ERROR Got nothing at all.

Recharge Status Check:

[http://bigerecharge.com/statusCheck.aspx?&reqId=\[REQUESTID\]&userid=\[USERID\]&tpin=\[TRANSACTIONID\]](http://bigerecharge.com/statusCheck.aspx?&reqId=[REQUESTID]&userid=[USERID]&tpin=[TRANSACTIONID])

Replace:

[REQUESTID]=Unique Id returned from system as response at time of recharge.

[USERID]= Mobile number of user register with our system.

[TRANSACTION ID]=4 Digit Transaction Id of user register with our system.

Recharge Status Check Example:

<http://bigerecharge.com/statusCheck.aspx?&reqId=635206478450386096&userid=9007650981&tpin=9505>

Response:

[STATUS] mob= [MOBILE] amt= [AMOUNT] OpTranId=
[OPTransId]

[STATUS]= Three types of status a) PENDING b) FAILED c) SUCCESS

You have to check status continuously if the status is "PENDING" until not showing "FAILED" or "SUCCESS"

[MOBILE]=Customer Mobile Number request for recharge.

[AMOUNT]=Recharge amount.
[OPTransId]=Operator Transaction Id

Exampe:

FAILED mob= 9836851100 amt= 10.00 OpTranId= 0

If Status request has any wrong information then Error
Message are:

1. ERROR Invalid Request ID.
2. ERROR Invalid Pin.
3. ERROR Invalid User Id.
4. ERROR Got nothing at all.

Automatic Recharge Response Url Parameter:

Please provide the status url for the response of recharge to the <http://allapi4u.com>

[http://www.yourdomain.com/pagename? status=\[STATUS\] &mob=\[MOBILE\]
&amt=\[AMOUNT\] &OpTranId=\[OPTransId\]&RequestId=\[REQUESTID\]](http://www.yourdomain.com/pagename?status=[STATUS]&mob=[MOBILE]&amt=[AMOUNT]&OpTranId=[OPTransId]&RequestId=[REQUESTID])

[STATUS]= Two types of status a) FAILED b) SUCCESS

[MOBILE]=Customer Mobile Number request for recharge.

[AMOUNT]=Recharge amount.

[OPTransId]=Operator Transaction Id

[REQUESTID]=Unique Id returned from system as response at time of recharge.

Service_provider	Code	Service_provider	Code	Service_provider	Code	Service_provider	Code
Aircel	2	AIRTEL DTH	51	MTS MBlaze	90	vodafone bill	83
Airtel	3	DISHTV	53	MTS MBrowse	89	Bsnl bill	82
BSNL	4	SUNDIRECT	54	Reliance NetConnect 1X	88	tata indicom bill	81
BSNL - Validity	5	TATA SKY	55	Reliance NetConnect 3G	87	docomo bill	80
Idea	12	VIDEOCON	56	Reliance NetConnect+	86	reliance cdma bill	79
Loop Mobile	98	Reliance Digital TV	57	Tata Photon Whiz	85	reliance GSM bill	78

MTS	99			Tata Photon+	84	airtel bill	77
Reliance CDMA	19					idea bill	76
Reliance GSM	18					uninor bill	75
S Tel	97						
Tata DOCOMO	25						
Docomo - Special	26						
Tata Indicom	92						
Tata Walky	91						
Uninor	31						
Uninor Special	32						
Videocon	96						
Videocon Special	95						
Virgin CDMA	94						
Virgin GSM	93						
Vodafone	37						